

Table 9-1

CCCS BUS CONTROL WORDS: TRANSMITTER

2

BIT NO.	CONTROL WORD 1 (frequency)	EXCITER DCU 010	ANT. CPLR. DCU 011 (490X-1)	ANT. CPLR. DCU 011 (490T-8)	PWR. AMP. DCU 100
0	Logic 1 (dialogic)	X	X	X	X
1	Logic 0 (radio	X	X	X	X
2	Logic 1 group)	X	X	X	X
3	DCU	X	X	X	X
4	1	X	X	X	X
5	ADDRESS	X	X	X	X
6	Logic 0 (sub-	X	X	X	X
7	Logic 0 address)	X	X	X	X
8	Parity	X	X	X	X
9	Not used				
10	10 MHz (2)	X	X	X	X
11	10 MHz (1)	X	X	X	X
12	1 MHz (8)	X	X	X	X
13	1 MHz (4)	X	X	X	X
14	1 MHz (2)	X	X	X	X
15	1 MHz (1)	X	X		X
16	100 KHz (8)	X	X		X
17	100 KHz (4)	X	X		X
18	100 KHz (2)	X	X		X
19	100 KHz (1)	X	X		X
20	10 KHz (8)	X			
21	10 KHz (4)	X			
22	10 KHz (2)	X			
23	10 KHz (1)	X			
24	1 KHz (8)	X			
25	1 KHz (4)	X			
26	1 KHz (2)	X			
27	1 KHz (1)	X			
28	0.1 KHz (8)	X			
29	0.1 KHz (4)	X			
30	0.1 KHz (2)	X			
31	0.1 KHz (1)	X			

NOTE: Numbers in parenthesis indicate ECD.
Symbol "X" indicates a bit is used by the DCU.