

Table 9-2

CCCS BUS CONTROL WORDS: TRANSMITTER

2

FIT NO.	CONTROL WORD 2 (mode)	EXCITER DCU 010	ANT. CPLR. DCU 011 (490X-1)	ANT. CPLR. DCU 011 (490T-8)	PWR. AMP. DCU 100
0	Logic 1 (dialogic)	X	X	X	X
1	Logic 0 (radio	X	X	X	X
2	Logic 1 group)	X	X	X	X
3	DCU	X	X	X	X
4		X	X	X	X
5	ADDRESS	X	X	X	X
6	Logic 0 (sub-	X	X	X	X
7	Logic 1 address)	X	X	X	X
8	Parity	X	X	X	X
9	Not used				
10	VOX enable	X			
11	Simplex enable	X			
12	B1 channel enable	X			
13	Not used				
14	A1 channel enable	X			
15	Not used				
16	Not used				
17	Self-test	X			
18	B2 channel enable	X			
19	CW enable	X			
20	AM enable	X			
21	Not used				
22	A2 channel enable	X			
23	Not used				
24	Not used				
25	Exciter tune	X	X	X	X
26	(Medium power)*				(X)
27	Low power				X
28	P. A. tune				X
29	Transmitter enable	X			X
30	Plate on				X
31	Key	X	X	X	X

*Can be sent only with 7404A-1. (OSCAR)

NOTE: Symbol "X" indicates a bit is used by the DCU.