

Table 9-3

CCCS CONTROL WORDS: TRANSMITTER

3

BIT NO.	CONTROL WORD 3 (carrier level) Exciter, DCU 010	CONTROL WORD 3 (A/D mux address) A/D Conv. or P. A. DCU	CONTROL WORD 4 (mon. request) All DCU's
0	Logic 1 (dialogic)	Logic 1 (dialogic)	Logic 1 (dialogic)
1	Logic 0 (radio	Logic 0 (radio	Logic 0 (radio
2	Logic 1 group)	Logic 1 group)	Logic 1 group)
3	Logic 0	DCU	DCU
4	Logic 1 (exciter)	ADDRESS	ADDRESS
5	Logic 0	ADDRESS	ADDRESS
6	Logic 1 (sub-	Logic 1 (sub-	Logic 1 (sub-
7	Logic 0 address)	Logic 0 address)	Logic 1 address)
8	Parity	Parity	Logic 0 (parity)
9	Not used	Not used	Logic 0
10	↑	Not used	↑
11	↑	A/D address (16)	↑
12	↑	A/D address (8)	↑
13	↑	A/D address (4)	↑
14	↑	A/D address (2)	↑
15	↑	A/D address (1)	↑
16	↑	Not used	↑
17	↓	↑	↓
18	↓	↑	↓
19	Not used	↑	↓
20	Carrier level (8)	↑	↓
21	Carrier level (4)	↑	↓
22	Carrier level (2)	↑	↓
23	Carrier level (1)	↑	↓
24	Not used	↑	↓
25	↑	↓	↓
26	↑	↓	↓
27	↑	↓	↓
28	↓	↓	↓
29	↓	↓	↓
30	↓	↓	↓
31	Not used	Not used	Logic 0

NOTE: Numbers in parenthesis indicate weighted BCD.